



HA360SA / HA360SA2.1 – Security Alert Signaler

The HA360SA / SA2.1 Security Alert will alert you to **ONE** of several types of alerts when linked to the HA360 Main unit. The Main unit receives a wireless signal from the HA360SA / SA2.1 and will flash a strobe, make a loud sound and vibrate a bed shaker. Once the Main unit receives the signal it will also send a signal to all HomeAware remote receivers.

The HA360SA / SA2.1 has 5 different door alerts (DOOR, FTDOOR, BKDOOR, DOOR3, DOOR4), a burglar help alert (HELP) and a motion alert (MOTION). The unit can connect to a NOAA weather radio (STORM), a home security (SECURIT). Every home security system is different, contact your provider for setup.

Installing Batteries

The HA360SA / SA2.1 Security Alert comes with two #357 silver oxide long lasting batteries that need to be installed into the bottom of the unit. Once installed the red light should light when the button is pushed. If the light does not show, you may have the batteries in backwards.

NOTE: The life expectancy for these batteries is typically about 2 years. Only replace the batteries with #357 silver oxide batteries. Do not use alkaline batteries.

Linking the HA360SA / SA2.1 to the Main Unit

This procedure will link your HA360SA / SA2.1 Security Alert to your HomeAware™ Main unit. The Main unit will also provide an alert to all HomeAware™ remote receivers. It is best to do the LINK procedure in the same room as close as possible to the HomeAware™ Main unit.


To link the unit to your HomeAware™ Main unit follow the steps below.

1. Press SET UP button on the Main unit and the word LINK will be shown on the display, press Enter.
2. LINK will begin blinking.
3. Remove the cover on the bottom of the HA360SA / SA2.1 and press and release the small black link button.
4. PICK DEVICE will display on the screen.
5. Repeatedly pressing the blue TONE button will allow you to select the alert you want displayed.
6. Press ENTER.
7. Once you have made your selection DONE will flash on the screen.

NOTE: There are two different versions of the HA360SA. The only difference in their operation is the position of the function selector switch.

HA360SA / SA2.1 Switch Locations and Positions

HA360SA – located on the bottom of the unit next to the link button



HA360SA2.1 – located on the back of the unit



There are three switch positions on the HA360SA and the HA360SA2.1., right to left

1. N.Closed

Normally closed* - Is a contact that flows current in its normal state. Switching it on will open the contact, causing it to not allow current flow.

NOTE: The normally closed position is used with external equipment that have normal closed outputs. This is typical of burglar alarm systems.

2. N.Open

Normally open* - Is a contact that does not flow current in its normal state. Switching it on will close the contact, causing it to allow current flow.

NOTE: The normally open position is used with external equipment that have normally open out. This typical of weather radios.

3. Door Chime

Is for when the barrel port is connected to the solenoid contacts of a door chime ringer. See note below.

NOTE: It is important that the switch not be on the open or closed positions if the unit is being connected to the door chime ringer. That could damage the unit if left this way for a long period of time.

WARNING: DO NOT EXPOSE THIS APPLIANCE TO RAIN OR MOISTURE TO PREVENT DAMAGE TO UNIT.

* Please check the user guide of the device you are connecting to the HA360SA / SA2.1 for the correct switch position.

For additional information on all HomeAware products please visit www.sonicalert.com.

FCC Requirements

This device complies with part 15 of the FCC rules, and with RSS-210 of Industry Canada. Operation is subject to the following two conditions; (1) This device might not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide responsible protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions manual, may cause harmful interference to radio communications. However, there is no guarantee that interference will not interfere in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment on and off, the user is encouraged to try to correct the interference by one or more of the following measures:

- i. Reorient or relocate the receiving antenna.
- ii. Increase the separation between the equipment and receiver.
- iii. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- iv. Consult the dealer or an experienced radio /TV technician for help

Modification not expressly approved by the manufacturer could void the user's authority to operate the equipment under FCC rules.

CANADIAN CERTIFICATION

This device complies with Industry Canada license exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

SONIC ALERT'S 1 YEAR LIMITED WARRANTY

The HomeAware™ HA360SA / SA2.1 is warranted against manufacturing defects in materials and workmanship for one (1) year from the date of purchase. Within this period Sonic Alert will repair or replace at our option the HomeAware™ HA360SA / SA2.1 without charge for parts and labor.

Simply contact our customer service department to obtain an RMA (return authorization number) and instructions on how to process your product for return. Call 1-248-577-5400 or e-mail to customerservice@sonicalert.com. You'll need a copy of your receipt to process the return authorization.

Sonic Alert Warranty
Stephenson Hwy., Suite 323, Troy, MI USA



Made in China
www.SonicAlert.com 1-248-577-5400